

M-800RCT/B

Remote audio control panel with touch display

The remote audio control shall include a 4.3" touch display for system adjustments and provide input/output signal routing. The device shall allow

pre-set controls. It shall contain a built in RD port IN (RJ45 connector) to connect to the M-8080D and M-804EX. It also contains a built in RD port OUT (RJ45 connector)

to connect to M-800RC or M-800RCT in daisy chain configuration. Power source of 24V DC (powered by M-8080D or M-804EX or external power supply). The device

size shall be 150 W x 115 H x 28 D mm (5.9" W x 4.53" H x 1.1"D). Weight shall be 0.28kg and have a finish of Polycarbonate + ABS resin in white or black colour.

The remote audio control panel with touch display shall be TOA model M-800RCT/B