

M-800RC/B

-----  
Remote audio control panel  
-----

The remote audio control panel shall control the volume of the audio system and provide input/output signal routing. It shall contain a built in RD port IN (RJ45 connector) for connection to M-8080D or M-804EX.

It shall contain a built in RD port OUT (RJ45 connector) for connection to M-800RC or M-800RCT in daisy chain configuration. The device shall have an LCD screen to display device information: ID, volume, and communication status. Power source of 24V DC (powered by M-8080D or M-804EX). The device size shall be 147 W x 86 H x 65 D mm (5.79" W x 3.39" H x 2.56"D). Weight shall be 0.3kg and have a finish of Polycarbonate + ABS resin in white or black colour.

The remote audio control panel shall be TOA model M-800RC/B