
Digital Power Amplifier Module 300W

Amplifier module with highly efficient digital class-D amplifier with an output power of 300 watts and internal low-loss voltage converter of advanced switching technology.

Lightweight through floating speaker line output without transformer.

Output voltage switchable between 50, 70 and 100 volts.

Fuse easily accessible from the back.

Ventilation with easy to clean filter.

Rated output power: 300 W (100 V)

Rated output voltage: 50 V, 70 V, 100 V

Frequency range: 40 – 16.000 Hz

Signal-to-noise ratio: > 100 dB (A-rated, 100 V)

THD: < 1% at 300 watts

Operating voltage: 31 VDC

Voltage range: 20 VDC to 34 VDC

Manufacturer: TOA

Type: VX-030DA